



PART - B

(5×13=65 Marks)

11. a) i) State and prove any four properties of DFT. (8)
 ii) Perform circular convolution of the following sequences $x_1(n) = \{1 \ 1 \ 2 \ 1\}$; $x_2(n) = \{1 \ 2 \ 3 \ 4\}$. (5)
 (OR)
- b) i) Mention the differences and similarities between DIT and DIF algorithms. (5)
 ii) Compute 4 point DFT of a sequence $x(n) = \{0 \ 1 \ 2 \ 3\}$ using DIF and DIT algorithms. (8)
12. a) i) Design an analog Butterworth filter for a given specifications. (7)
 $0.9 \leq |H(j\Omega)| \leq 1$ for $0 \leq \Omega \leq 0.2\pi$.
 $|H(j\Omega)| \leq 0.2$ for $0.4\pi \leq \Omega \leq \pi$.
 ii) Apply impulse invariant method and find $H(z)$ for $H(s) = \frac{s+a}{(s+a)^2 + b^2}$. (6)
 (OR)
- b) i) Apply bilinear transformation to $H(s) = \frac{2}{(s+1)(s+2)}$ with $T = 1$ sec and find $H(z)$. (6)
 ii) Explain the Lattice-Ladder structure with neat diagram. (7)
13. a) Write the expression for the frequency response of Rectangular window and Hamming window and explain. (7+6)
 (OR)
- b) Determine the filter coefficients $h(n)$ obtained by sampling
 $H_d(e^{j\omega}) = e^{-j(N-1)\omega/2} \quad 0 \leq |\omega| \leq \frac{\pi}{2}$
 $= 0 \quad \frac{\pi}{2} \leq |\omega| \leq \pi$
 for $N = 7$. (13)
14. a) The output signal of an A/D convertor is passed through a first order low pass filter, with transfer function given by $H(z) = \frac{(1-a)z}{z-a}$ for $0 \leq a \leq 1$. Find the steady state output noise power due to quantization at the output of the digital filter. (13)
 (OR)
- b) Briefly explain the following :
 i) Coefficient quantization error. (4)
 ii) Product quantization error. (4)
 iii) Truncation and Rounding. (5)



15. a) Explain sampling rate conversion by a rational factor and derive input-output relation in both time and frequency domain. (13)
 (OR)
- b) With neat required diagrams explain any two applications of adaptive filtering. (6+7)

PART - C

(1×15=15 Marks)

16. a) An FIR Filter is given by the difference equation

$$y(n) = 2x(n) + \frac{4}{5}x(n-1) + \frac{3}{2}x(n-2) + \frac{2}{3}x(n-3)$$

Determine its lattice form. (15)

(OR)

- b) How is signal scaling used to prevent overflow limit cycle in the digital filter implementation? Explain with an example. (15)